S16 Firmware Update

Version 2.4 - (15 March 2019)

The firmware update 2.4 for S16 fixes a specific performance issue with the AES50 channel forwarding system.

The firmware 2.3 Daisy Chain Master configuration allows using multiple stageboxes as high-perfomance recording interfaces with the KT-USB DN9630 AES50 to USB Converter. In addition to ADAT and P16 Ultranet multi-channel output, this configuration allows to connect up to 24 analog XLR outputs and 48 analog XLR inputs to the DN9630 USB interface.

The firmware update can easily be done via USB using a Windows PC/laptop computer. Please follow the update instructions at the end of this document.

This new S16 Firmware version contains:

New features

- n/a

Improvements

- fixes an issue with AES50 output B channel forwarding after start up

Requirements:

Behringer X32 / Midas series console firmware 2.10 or higher recommended for optimal use with S16 firmware 2.4.

Windows (10, 7 or 8.1) PC with USB connector and administrator account required for running the updater executable (S16update_2-3.exe).

Download Firmware Updater:

S16_Firmware_Update_2.4.zip

Update Process:

1. Download and unpack the updater zip file from behringer.com on your Windows PC
2. Connect the S16 USB port to your PC using a standard USB cable (type A -- type B)
3. Hold the CONFIG button depressed while switching the S16 on
4. The S16 display will show the current firmware version on its display
5. Make sure you have started your Windows session with Administrator access, then start the updater executable
6. The terminal window will inform you about the update progress. Wait approximately 1 min until it shows completed.
7. Disconnect the USB link and switch the S16 power off / on
8. If you wish, you may check if the update has successfully been loaded by holding the CONFIG button while power cycling the S16, again.
9. Note, that the display will only show the firmware version while being connected via USB.

© Music Tribe Global Brands Ltd. All rights reserved.
All information in this document is subject to change without any further notice.