

# Behringer

## 2600

Semi-Modular Analog Synthesizer with  
3 VCOs and Multi-Mode VCF in  
8URack-Mount Format



## 2600 SysEX Pitch Bend Range Information

This message is used to change the MIDI pitch bend range:

MIDI Bytes (Hex)	Description
F0	SysEX status byte
00 20 32	Manufacturer SysEX ID Number (Behringer GmbH)
00 01 0B	Model ID: 00 01 0B for 2600
ID	Device ID(0-127)
11	Packet Type Information Message Code (PKT)
D0 ... D1	D0: Value 00~0C à (+/-)0~12 Semitones (Please Refer to Appendix A Table 2) Default Value: 02

Channel Message	En	bb	bb	[0, 3FFF]	Pitch bend
-----------------	----	----	----	-----------	------------

Example:

Set pitch bend range to 2 semitones.	F0 00 20 32 00 01 0B ID 11 02 00 F7
--------------------------------------	-------------------------------------