


Thank you for showing your confidence in us by purchasing the BEHRINGER INTELLIGATE IG9. This ultimate effects pedal is specifically designed to achieve super-effective noise suppression without signal deterioration. It ensures high signal integrity through a very fast attack time, program-adaptive release time and frequency-selective noise suppression.

A noise gate increases the dynamic range of a signal by suppressing unwanted noise which is cut out when the instrument signal drops below a certain threshold level. Furthermore, the IG9 has a selectable filter cut-off point for frequency-selective noise suppression ensuring inaudible dynamics enhancement and ultra-transparent tone.

1. CONTROLS



Top view

- 1 Use the **THRESHOLD** switch to select a threshold range which suits your signal. In the upper position (HIGH) the sensitivity is high and the gate only cuts out very low-level signal portions. In the lower position (LOW) the sensitivity is low and the gate is more often cutting off.
- 2 Turn the **THRESHOLD** control to precisely set the threshold value above which the signal will remain unaffected.
- 3 The **GATE** selector determines the frequency range that is cleaned by the IG9. Set it to HIGH to gate out the signal of instruments with high-frequency boost as in the case with clean guitar and keyboard. Use the MID position to clean the signal of sources with midrange-frequency boost as, for example, with distorted guitar. In both cases low-frequency signals will remain unaffected. Select the FULL position for signals with hum or buzz problems like the output of a guitar effects rack. The intensity of the GATE LED above the selector indicates the level of noise reduction.
- 4 The LED illuminates when the effect is activated. It also serves as a battery level indicator.
- 5 Depress the footswitch to activate/deactivate the effect.
- 6 Use this 1/4" TS **IN** connector to plug in the instrument cable.
- 7 The 1/4" TS **OUT** connector sends the signal to your amp.

Use the DC IN connection to plug in a 9 V power supply (not included).

To install or replace the 9 V battery (not included), remove the bottom side of the unit taking the four screws off.

The IG9 has no on/off switch. As soon as you connect the jack to the in connector, the IG9 is switched on. When the IG9 is not being used, remove the jack from the in connector to extend the battery life.

The **SERIAL NUMBER** is located on the bottom side of the device.

2. WARRANTY

For our current warranty terms, please refer to our website at <http://www.behringer.com>.

3. SPECIFICATIONS

In	
Connector	1/4" TS
Impedance	1 MΩ
Out	
Connector	1/4" TS
Impedance	1 kΩ
Power supply	
Power consumption	15 mA BEHRINGER PSU-SB
Mains connection	
Connector	mains plug
Voltage	100 V - 230 V, 50/60 Hz
Device connection	
Connector	2 mm DC jack, negative center
Voltage	9 V---
Current	100 mA regulated
Battery power supply	
Battery	9 V type 6LR61
Power consumption	15 mA
Dimensions/weight	
Dimensions (H x W x D)	approx. 56 mm (2 1/5") x 113 mm (4 2/5") x 69 mm (2 2/3")
Weight	approx. 0.24 kg (0.53 lbs)

BEHRINGER is constantly striving to maintain the highest professional standards. As a result of these efforts, modifications may be made from time to time to existing products without prior notice. Specifications and appearance may therefore differ from those listed or shown.

4. SAFETY INSTRUCTIONS

Do not use near water, or install near heat sources. Use only authorized attachments/accessories. Do not service product yourself. Contact our qualified servicing personnel for servicing or repairs, especially when power supply cord or plug is damaged.

No utilizar cerca de agua o instalar cerca de fuentes de calor. Utilice sólo accesorios y aditamentos autorizados. No intente reparar el producto usted mismo. Contacte a nuestro personal técnico cualificado para servicio y reparaciones, especialmente cuando la fuente o el cable de alimentación estén dañados.

Не эксплуатируйте прибор вблизи от источников воды и тепла. Применяйте только авторизованные дополнительные устройства. Никогда не ремонтируйте прибор самостоятельно. Ремонт может производить только квалифицированный специализированный персонал, особенно при повреждениях сетевого провода или сетевой вилки.

水分の近くや、ヒーターなど熱気のある場所では使用しないでください。正式に認可された付属品のみを使用してください。製品はご自分では決して修理せず、特に電源コードもしくはプラグが損傷した場合には、必ず製品サービスおよびリペアの資格を有した当社の担当員にご相談ください。

不要在靠近水源的地方使用，或在靠近热源的地方安装。只使用经过许可的附件 / 配件。不要自己进行产品维修，尤其是当电源线或插座损坏的时候，请联系我们的专业服务人员有关产品维修事宜。

Die deutsche Anleitung ist erhältlich @ www.behringer.com
Manuel francophone en téléchargement sur www.behringer.com
Manual en español disponible en www.behringer.com
Manuali italiani disponibili @ www.behringer.com
Русскоязычное руководство @ www.behringer.com
Polska instrukcja dostępna jest pod adresem @ www.behringer.com
Nederlandse handleiding beschikbaar @ www.behringer.com
Suomenkielinen käyttöohje saatavilla osoitteesta www.behringer.com
Svensk manual finns tillgänglig på www.behringer.com
Dansk vejledning findes på @ www.behringer.com
Manual português disponível @ www.behringer.com
Ελληνικό εγχειρίδιο υπάρχει διαθέσιμο στη διεύθυνση www.behringer.com
日本語版マニュアル@ www.behringer.com
使用说明书可在 www.behringer.com 下载

Technical specifications and appearance subject to change without notice. The information contained herein is correct at the time of printing. BEHRINGER accepts no liability for any loss which may be suffered by any person who relies either wholly or in part upon any description, photograph or statement contained herein. Colours and specification may vary slightly from product. Products are sold through our authorised dealers only. Distributors and dealers are not agents of BEHRINGER and have absolutely no authority to bind BEHRINGER by any express or implied undertaking or representation. No part of this manual may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording of any kind, for any purpose, without the express written permission of BEHRINGER International GmbH. BEHRINGER, the BEHRINGER logo and JUST LISTEN are trademarks of BEHRINGER. ALL RIGHTS RESERVED. © 2008 BEHRINGER International GmbH, Hanns-Martin-Schleyer-Str. 36-38, 47877 Willich-Münchheide II, Germany. Tel. +49 2154 9206 0, Fax +49 2154 9206 4903